



GFE-ZEOS-PROGRAMMER

Portable Programmer

This equipment enables manual address assignment to all self-programmable devices. It should be used during maintenance and installation as an alternative to GFE's addressable panels ASET mode. Additionally it also allows installer to read address of the device and read its analogue value. A larger battery life is obtained with use of lithium batteries, which can be recharged through available USB port.

LED Status

Green - Programmer is working correctly.
 Green Flashing - Battery is charging.
 Yellow - Selected function in progress.
 Red - Internal fault.
 Red Flashing - Low battery.

Keypad Operation

OK	> Power ON
OK (2 seconds)	> Power OFF
UP	> Increase Address
DOWN	> Decrease Address
OK	> Program Address
UP & OK	> Read Analogue Value
UP & DOWN	> Read Address
DOWN	> Back

TECHNICAL SPECIFICATIONS

OPERATING VOLTAGE	3.3 V (DC)
CHARGE CURRENT	100 mA max.
CHARGE VOLTAGE 5	V DC (Mini USB)
CHARGE DURATION	2 hours (max.)
AUTO POWER OFF A	fter 2 minutes
AUTONOMY	+500 operations
MAX. HUMIDITY	95% RH Non-Condensing
OPERATING TEMPERATURE	0°C to 40°C
DIMENSIONS	86 (D) x 25 (H) mm
WEIGHT	172 g

ORDER CODE

GFE-ZEOS-PROGRAMMER

PORTABLE PROGRAMMER

Global Fire Equipment SA

Sítio dos Barrabés, Armazém Nave Y, Caixa Postal 908-Z
 8150-016 São Brás de Alportel. PORTUGAL

Telephone: (00351) 289 896 560 / Email: info@globalfire-equipment.com / Web: www.globalfire-equipment.com



GSS GROUP