

RF 868MHZ SYSTEM KIT FOR SHOPS



Reference: 5249

This radiofrequency kit allows door opening from distance remotely through a RF transmitter. The door requires a receiver that can be placed indoor (perfect for shops and/or garages) or outdoors.

The...

DESCRIPTION

This radiofrequency kit allows door opening from distance remotely through a RF transmitter. The door requires a receiver that can be placed indoor (perfect for shops and/or garages) or outdoors.

The transmitter has an exclusive code chosen by the user, offering the maximum security. It reaches up to 100 metres distance thanks to the frequency ratio of 868Mhz.

With the APS (Approaching System) transmission system, one can activate the button on the transmitter whilst being outside of the receptor range.

The transmitter will transmit the signal constantly until the user comes within range of the reader, when the user approximates to the door and until the door is open.

The transmitter includes 2 pushbuttons that allow to opening the door and activate a second function as turning on/off the lighting or the air conditioner, opening a second door...

The kit includes a ref. 5250 RF receiver up to 500 codes, power supply ref. 4802 and 3 Keysingle Mini transmitters ref. 5259.

TECHNICAL SPECIFICATIONS

BASIC-2B

Frequency: 868,35MHz

Codification: High security changing code

Memory: 500 codes

Number of relays: 2 relay (Relay 1 (monostable) y Relay 2 (monostable/bistable))

Power Supply: 12/24Vac/dc $\pm 10\%$

Relay contacts: 1A

Consumption in standby / Consumption functioning: 60mA / 90mA

Functional temperature: -20°C to +85°C

Tightness: IP54 (IP65 with gland)

FERMAX

Dimensions: 63x74x25mm

Box dimensions: 82x190x40mm

Weight: 0,900246 kg

Size of product when packed: 7,5x23x17,8 cm

EAN 13: 8424299052496

Included products



RF KEYSINGLE MINI REMOTE CONTROL

Ref: 5259

RF Emitter with programmable security code. It allows to open doors from a distance up to 100 metres. It allows to opening doors on accesses with...

[+ INFO](#)



RF BASIC-2B RECEIVER 12- 24V

Ref: 5250

Autonomous receiver supplied by 12/24Vac/dc that allows to manage up to 500 codes from 868Mhz RF transmitters. A channel (emitter pushbutton) can...

[+ INFO](#)



P.S.U. DIN4 230VAC/12VAC-1A

Ref: 4802

Used to power the different equipment in a Fermax installation.

Constructed in self-extinguishing VO material. Includes a set of covers to protect the...

[+ INFO](#)