



Installation Devices / Power supplies and complements

Product Code

F04840

P.S.U. DIN-6  
100-240VAC/24VDC-2A

Reference

4840

EAN

8424299048406

## Description.

### Description

DIN-6 rail format for easy installation inside an electrical equipment box, or can can be screwed directly onto the wall.

Used to power the different equipment in a Fermax installation.

Constructed in self-extinguishing VO material.

Includes a set of covers to protect the connection terminals.

The power supply cannot be connected directly to the bus, given the characteristics of the Bus 2 or DUOX systems, since the power feed and the data go through the same wires. This requires the connection module.

The power supply connection module should be connected directly to the bus with the shortest cable distance possible.

This module prevents the power supply from disrupting the operation of the rest of the signals that circulate through the system, and it will also allow for more power supplies to be connected if required by the system.

### Technical Details

With two function indicator LEDs:

- ON LED lit: indicates that the power supply is working.
- OVERLOAD LED lit: indicates maximum current exceeded (it will be necessary to reduce the installation load or add additional power supply/supplies).
- ON LED+OVERLOAD blinking: indicates short circuit.

#### Power:

- BUS 2 system: 24 VDC
- DUOX system: 18 VDC

Output current depends on the power supply connected. Power supplies of up to 3.5 A.

BUS 2 system input voltage: 24 VDC.

DUOX system input voltage: 18 VDC.

#### Details.

---

Weight (kg)

0.3466

Packaging measurements

(height x width x depth) cm

6,5x11,3x9,6

Video Door Entry system

Technologie

DUOX

#### Manuals

970154 Fuente Alimentacion 24Vdc Ref 4840 V07\_20.pdf

#### Declaration of conformity

DOCF04840EN.pdf